

PSU Series Specifications

| Model | | PSU | 6-800 | 12.5-480 | 20-304 | 40-152 | 60-100 | 100-60 | 150-40 | 300-20 | 400-15.2 | 600-10.4 |
|---------------------------|--|-----|-------|----------|--------|--------|--------|--------|--------|--------|----------|----------|
| Rated output voltage (*1) | | V | 6 | 12.5 | 20 | 40 | 60 | 100 | 150 | 300 | 400 | 600 |
| Rated output current (*2) | | A | 800 | 480 | 304 | 152 | 100 | 60 | 40 | 20 | 15.2 | 10.4 |
| Rated output power | | W | 4800 | 6000 | 6080 | 6080 | 6000 | 6000 | 6000 | 6000 | 6080 | 6240 |

| Programming and Measurement (RS-232/485, USB, LAN, GPIB) | PSU | 6-800 | 12.5-480 | 20-304 | 40-152 | 60-100 | 100-60 | 150-40 | 300-20 | 400-15.2 | 600-10.4 |
|---|------------|--------------|-----------------|---------------|---------------|---------------|---------------|---------------|---------------|-----------------|-----------------|
| Output voltage programming accuracy | 0.05% + | mV | 3 | 6.25 | 10 | 20 | 30 | 50 | 75 | 150 | 200 |
| Output current programming accuracy | 0.2% + | mA | 800 | 480 | 304 | 152 | 100 | 60 | 40 | 20 | 15.2 |
| Output voltage programming resolution | | mV | 0.2 | 0.4 | 0.7 | 1.3 | 2 | 3.4 | 5.2 | 10.2 | 13.6 |
| Output current programming resolution | | mA | 24 | 16 | 10 | 4.8 | 3.2 | 2 | 1.36 | 0.76 | 0.52 |
| Output voltage measurement accuracy | 0.1% + | mV | 6 | 12.5 | 20 | 40 | 60 | 100 | 150 | 300 | 400 |
| Output current measurement accuracy | 0.2% + | mA | 1600 | 960 | 608 | 304 | 200 | 120 | 80 | 40 | 30.4 |
| Output voltage measurement resolution | | mV | 0.2 | 0.4 | 0.7 | 1.3 | 2 | 3.4 | 5.2 | 10.2 | 13.6 |
| Output current measurement resolution | | mA | 24 | 16 | 10 | 4.8 | 3.2 | 2 | 1.36 | 0.76 | 0.52 |

| Environmental Conditions | PSU | 6-800 | 12.5-480 | 20-304 | 40-152 | 60-100 | 100-60 | 150-40 | 300-20 | 400-15.2 | 600-10.4 |
|--------------------------|-----|-------|---------------------------------|--------|--------|--------|--------|--------|--------|----------|----------|
| Operaing temperature | | | 0°C to 50°C (*14) | | | | | | | | |
| Storage temperature | | | -25°C to 70°C | | | | | | | | |
| Operating humidity | | | 20% to 85% RH; No condensation | | | | | | | | |
| Storage humidity | | | 90% RH or less; No condensation | | | | | | | | |
| Altitude | | | Maximum 2000m | | | | | | | | |

| General Specifications | PSU | 6-800 | 12.5-480 | 20-304 | 40-152 | 60-100 | 100-60 | 150-40 | 300-20 | 400-15.2 | 600-10.4 |
|------------------------|----------------|-------|---|--------|--------|--------|--------|--------|--------|----------|----------|
| Weight | main unit only | kg | Less than 37.4kg | | | | | | | | |
| Dimensions | (W×H×D) | mm^3 | 423×174.4×447.2 | | | | | | | | |
| Cooling | | | Forced air cooling by internal fan. | | | | | | | | |
| EMC | | | | | | | | | | | |
| Safety | | | | | | | | | | | |
| Withstand voltage | | | AC to Chassis : 1500Vac / 1min AC to Output terminal : 3000Vac / 1min Vout≤150V Output terminal to Chassis : 1000Vdc / 1min 150<Vout≤600 Output terminal to Chassis : 1500Vdc / 1min | | | | | | | | |
| Insulation resistance | | | Chassis and output terminal; chassis and AC input; AC input and output terminal: 100MΩ or more (DC 1000V) | | | | | | | | |

Notes:

(*1) Minimum voltage is guaranteed to maximum 0.2% of the rated output voltage.

(*2) Minimum current is guaranteed to maximum 0.4% of the rated output current.

(*3) Single phase 200V models: 170-265Vac. Three phase 200V models : 180-253Vac. Three phase 400V models : 360-440Vac.

(*4) From No-load to Full-load, constant input voltage. Measured at the sensing point in Remote Sense.

(*5) Measured at rated output voltage and current with JEITA RC-9131B probe

(*6) Measurement frequency bandwidth is 10Hz to 20MHz.

(*7) Measurement frequency bandwidth is 5Hz to 1MHz.

(*8) From 10% to 90% of rated output voltage, with rated resistive load.

(*9) From 90% to 10% of rated output voltage, with rated resistive load.

(*10) Time for output voltage to recover within 2% of its rated output for a load change from 50 to 100% of its rated output current. Voltage set point from 10% to 100% of rated output.

(*11) For load voltage change, equal to the unit voltage rating, constant input voltage.

(*12) For 6V~20V model the ripple is measured at 2V ~ rated output voltage and full output current. For other models, the ripple is measured at 10 ~ 100% output voltage and full output current.

(*13) Single phase and three phase 200V models : at 200Vac input voltage. Three phase 400V models : at 400Vac input voltage. At rated output power.

(*14) If install the front panel filter kit, the temperature is guaranteed to 40°C.